



M-802RC

Designed for exclusive use with the M-8080D, the M-802RC Remote Audio Control Panel with two audio output has a volume/routing control knob.



Article number:M-802RC-EB

Specifications

| | |
|-----------------------|--|
| Controls | Volume / Routing |
| Indicator | LC-Display Displays device information: ID, Volume, communication status |
| Power source | 24 V DC Powered by M-8080D or M-804EX or external |
| Power source | 24 V DC Powered by M-8080D or M-804EX or external |
| Frequency response | 20 Hz - 20 kHz |
| Frequency response | 20 Hz - 20 kHz |
| Distortion | < 0.01 % |
| S/N ratio | 105 dB (A weighted) |
| Indicator | LC-Display Displays device information: ID, Volume, communication status |
| Crosstalk | 79 dB |
| S/N ratio | 105 dB (A weighted) |
| Inputs | RD In: Transmits and receives AES3 digital audio plus control data Connect to M-8080D or M-804EX, RJ45 connector |
| Outputs | Audio Output: Line output 1 - 2: 0 dBV, 1.8kOhm, Maximum output 20dBu (7.75V), electronic balanced, screw terminal (3 pins x 2) |
| Controls | Volume / Routing |
| Sampling frequency | 48 kHz, 24 bit |
| Distortion | < 0.01 % |
| Finish | Polycarbonate, ABS resin, traffic white (RAL 9016 or equivalent), Panel. |
| Operating humidity | 90% RH or less (no condensation) |
| Operating temperature | 0°C to +40°C |



M-802RC

Appearance